

Please type a plus sign (+) inside this box → ☐

PTO/SB/05 (4/98)
Approved for use through 09/30/2000. OMB 0651-0032
Patent and Trademark Office: U.S. DEPARTMENT OF COMMERCE

Under the Paperwork Reduction Act of 1995, no persons are required to respond to a collection of information unless it displays a valid OMB control number.

UTILITY PATENT APPLICATION TRANSMITTAL

(Only for new nonprovisional applications under 37 C.F.R. § 1.53(b))

Attorney Docket No. 473P09US
First Inventor or Application Identifier Stinson, Michael R.
Title Microphone Array Diffracting Structure
Express Mail Label No.

APPLICATION ELEMENTS

See MPEP chapter 600 concerning utility patent application contents.

1. ☒ * Fee Transmittal Form (e.g., PTO/SB/17)
(Submit an original and a duplicate for fee processing)
2. ☒ Specification [Total Pages 42]
(preferred arrangement set forth below)
 - Descriptive title of the Invention
 - Cross References to Related Applications
 - Statement Regarding Fed sponsored R & D
 - Reference to Microfiche Appendix
 - Background of the Invention
 - Brief Summary of the Invention
 - Brief Description of the Drawings (if filed)
 - Detailed Description
 - Claim(s)
 - Abstract of the Disclosure
3. ☒ Drawing(s) (35 U.S.C. 113) [Total Sheets 13]
4. Oath or Declaration [Total Pages 3]
 - a. ☒ Newly executed (original or copy)
 - b. ☐ Copy from a prior application (37 C.F.R. § 1.63(d))
(for continuation/divisional with Box 16 completed)
 - i. ☐ DELETION OF INVENTOR(S)
Signed statement attached deleting inventor(s) named in the prior application, see 37 C.F.R. §§ 1.63(d)(2) and 1.33(b).

* NOTE FOR ITEMS 1 & 13: IN ORDER TO BE ENTITLED TO PAY SMALL ENTITY FEES, A SMALL ENTITY STATEMENT IS REQUIRED (37 C.F.R. § 1.27), EXCEPT IF ONE FILED IN A PRIOR APPLICATION IS RELIED UPON (37 C.F.R. § 1.28).

ADDRESS TO:

Assistant Commissioner for Patents
Box Patent Application
Washington, DC 20231

5. ☐ Microfiche Computer Program (Appendix)
6. Nucleotide and/or Amino Acid Sequence Submission (if applicable, all necessary)
 - a. ☐ Computer Readable Copy
 - b. ☐ Paper Copy (identical to computer copy)
 - c. ☐ Statement verifying identity of above copies

ACCOMPANYING APPLICATION PARTS

7. ☒ Assignment Papers (cover sheet & document(s))
8. ☐ 37 C.F.R. § 3.73(b) Statement of Power of Attorney (when there is an assignee)
9. ☐ English Translation Document (if applicable)
10. ☐ Information Disclosure Statement (IDS)/PTO-1449 [Copies of IDS Citations]
11. ☐ Preliminary Amendment
12. ☒ Return Receipt Postcard (MPEP 503)
(Should be specifically itemized)
13. ☐ * Small Entity Statement filed in prior application, Status still proper and desired (PTO/SB/09-12)
14. ☐ Certified Copy of Priority Document(s) (if foreign priority is claimed)
15. ☐ Other:

16. If a CONTINUING APPLICATION, check appropriate box, and supply the requisite information below and in a preliminary amendment:

☐ Continuation ☐ Divisional ☐ Continuation-in-part (CIP)

of prior application No. _____

Prior application information: Examiner _____

Group / Art Unit: _____

For CONTINUATION or DIVISIONAL APPS only: The entire disclosure of the prior application, from which an oath or declaration is supplied under Box 4b, is considered a part of the disclosure of the accompanying continuation or divisional application and is hereby incorporated by reference. The incorporation can only be relied upon when a portion has been inadvertently omitted from the submitted application parts.

17. CORRESPONDENCE ADDRESS

☐ Customer Number or Bar Code Label

or ☒ Correspondence address below

(Insert Customer No. or Attach bar code label here)

Name	Pascal & Associates				
Address	P.O. Box 11121 Station H				
City	Nepean	State	Ontario	Zip Code	K2H 7T8
Country	Canada	Telephone	(613) 820-1366	Fax	(613) 820-1553

Name (Print/Type)	Harold C Baker	Registration No. (Attorney/Agent)	19333
Signature		Date	Dec 16, 1999

Burden Hour Statement: This form is estimated to take 0.2 hours to complete. Time will vary depending upon the needs of the individual case. Any comments on the amount of time you are required to complete this form should be sent to the Chief Information Officer, Patent and Trademark Office, Washington, DC 20231. DO NOT SEND FEES OR COMPLETED FORMS TO THIS ADDRESS. SEND TO: Assistant Commissioner for Patents, Box Patent Application, Washington, DC 20231.

MICROPHONE ARRAY DIFFRACTING STRUCTURE

Field of the Invention

5 The present invention relates to microphone technology and specifically to microphone arrays which can achieve enhanced acoustic directionality by a combination of both physical and signal processing means.

10 Background of the Invention

Microphone arrays are well known in the field of acoustics. By combining the outputs of several microphones in an array electronically, a directional sound pickup pattern can be achieved. This means that sound arriving from a small range of directions is emphasized while sound coming from other directions is attenuated. Such a capability is useful in areas such as telephony, teleconferencing, video conferencing, hearing aids, and the detection of sound sources outdoors. However, practical considerations mitigate against physically large arrays. It is therefore desirable to obtain as much acoustical directionality out of as small an array as possible.

Normally, reduced array size can be achieved by utilizing superdirective approaches in the combining of microphone signals rather than the more conventional delay and sum beamforming usually used in array signal processing. While superdirective approaches do work, the resulting array designs can be very sensitive to the effects of microphone self noise and errors in matching microphone amplitude and phase responses.

A few approaches have been attempted in the field to solve the above problem. Elko, in U.S. Patent 5,742,693 considers the improved directionality obtained by placing a first order microphone near a plane baffle, giving an effective second order system. Unfortunately, the system described is unwieldy. Elko notes that when choosing baffle dimensions, the largest possible baffle is most desirable. Also, to achieve a second order response, Elko notes that the baffle size should be in the order of at least one-half a wavelength of the desired signal. These requirements render Elko unsuitable for applications requiring physically small arrays.

Bartlett et al, in U.S. Patent 5,539,834 discloses achieving a second order effect from a first order microphone. Bartlett achieves a performance enhancement by using a reflected signal from a plane baffle. However, Bartlett does not achieve the desired directivity required in some applications. While Bartlett would be useful as a microphone in a cellular telephone handset, it cannot be readily adapted for applications such as handsfree telephony or teleconferencing in which high directionality is desirable.

Another approach, taken by Kuhn in U.S. Patent 5,592,441, uses forty-two transducers on the vertices of a regular geodesic two frequency icosahedron. While Kuhn may produce the desired directionality, it is clear that Kuhn is quite complex and impractical for the uses envisioned above.

Another patent, issued to Elko et al, U.S. Patent 4,802,227, addresses signal processing aspects of

microphone arrays. Elko et al however, utilizes costly
signal processing means to reduce noise. The signal
processing capabilities required to keep adaptively
calculating the required real-time analysis can be
prohibitive.

A further patent, issued to Gorike, U.S. Patent
4,904,078 uses directional microphones in eyeglasses to
assist persons with a hearing disability receiving aural
signals. The directional microphones, however, do not
allow for a changing directionality as to the source of
the sound.

The use of diffraction can effectively increase the
aperture size and the directionality of a microphone
array. Thus, diffractive effects and the proper design
of diffractive surfaces can provide large aperture sizes
and improved directivity with relatively small arrays.
When implemented using superdirective beamforming, the
resulting array is less sensitive to microphone self
noise and errors in matching microphone amplitude and
phase responses. A simple example of how a diffracting
object can improve the directional performance of a
system is provided by the human head and ears. The
typical separation between the ears of a human is 15 cm.
Measurements of two-ear correlation functions in
reverberant rooms show that the effective separation is
more than double this, about 30 cm, which is the ear
separation around a half-circumference of the head.

Academic papers have recently suggested that
diffracting structures can be used with microphone
arrays. An oral paper by Kawahara and Fukudome,
("Superdirectivity design for a sphere-baffled
microphone", J. Acoust. Soc. Am. 130,2897, 1998),

suggests that a sphere can be used to advantage in beamforming. A six-microphone configuration mounted on a sphere was discussed by Elko and Pong, ("A steerable and variable 1st order differential microphone array", Intl. Conf. On Acoustics, Speech and Signal Processing, 1997), noting that the presence of the sphere acted to increase the effective separation of the microphones. However, these two publications only consider the case of a rigid intervening sphere.

What is therefore required is a directional microphone array which is relatively inexpensive, small, and can be easily adapted for electro acoustic applications such as teleconferencing and hands free telephony.

Summary of the Invention

The present invention uses diffractive effects to increase the effective aperture size and the directionality of a microphone array along with a signal processing method which generates time delay weights, amplitude and phase delay adjustments for signals coming from different microphones in the array.

The present invention increases the aperture size of a microphone array by introducing a diffracting structure into the interior of a microphone array. The diffracting structure within the array modifies both the amplitude and phase of the acoustic signal reaching the microphones. The diffracting structure increases acoustic shadowing along with the signal's travel time around the structure. The diffracting structure in the array effectively increases the aperture size of the array and thereby increases the

directivity of the array. Constructing the surface of the diffracting structure such that surface waves can form over the surface further increases the travel time and modifies the amplitude of the acoustical signal thereby allowing a larger effective aperture for the array.

In one embodiment, the present invention provides a diffracting structure for use with a microphone array, the microphone array being comprised of a plurality of microphones defining a space generally enclosed by the array wherein a placement of the structure is chosen from the group comprising the structure is positioned substantially adjacent to the space; and at least a portion of the structure is substantially within the space; and wherein the structure has an outside surface.

In another embodiment, the present invention provides a microphone array comprising a plurality of microphones constructed and arranged to generally enclose a space; a diffracting structure placed such that at least a portion of the structure is adjacent to the space wherein the diffracting structure has an outside surface.

A further embodiment of the invention provides a method of increasing an apparent aperture size of a microphone array, the method comprising; positioning a diffraction structure within a space defined by the microphone array to extend a travel time of sound signals to be received by microphones in the microphone array, generating different time delay weights, phases, and amplitudes for signals from each microphone in the microphone array, applying said time delay weights to said sound signals received by each microphone in the

microphone array wherein the diffraction structure has a shape, said time delay weights are determined by analyzing the shape of the diffraction structure and the travel time of the sound signals.

5 Another embodiment of the invention provides a microphone array for use on a generally flat surface comprising; a body having a convex top and an inverted truncated cone for a bottom, a plurality of cells located on a surface of the bottom for producing an
10 acoustic impedance and a plurality of microphones located adjacent to the bottom.

Brief Description of the Drawings

A better understanding of the invention will be
15 obtained by considering the detailed description below, with reference to the following drawings in which:

Figure 1 is a diagram of a circular microphone array detailing the variables used in the analysis below;

20 Figure 2 is a diagram of a tetrahedral microphone array;

Figure 3 illustrates a directional beam response for a circular array.

Figure 4 illustrates a circular microphone array
25 with a spherical diffracting structure within the array;

Figure 5 illustrates a bi-circular microphone array with an oblate spheroid shaped diffracting structure inside the array;

Figure 6 illustrates the beamformer response for a
30 circular array with a spherical diffracting structure (solid curve) and the response for a circular array without a diffracting structure (dashed curve);

Figures 7A to 24A illustrates top views of some possible diffracting structures and microphone arrays.

Figures 7B to 24B illustrate corresponding side view of the diffracting structures of Figures 7A to 24A.

5 Figure 25 is a plot comparing the directivity of a circular array having a diffracting structure within the array with the directivity of the same circular array without the diffracting structure.

10 Figure 26 illustrates the construction of a surface wave propagating surface for the diffracting structures.

Figure 27 plots the surface wave phase speed for a simple celled construction as pictured in Fig 17; and

15 Figures 28-31 illustrate different configurations for coating the diffracting surface.

Figure 32 is a plot of the directional beam response for a hemispherical diffracting structure. The plots for a rigid and a soft diffracting structure are plotted on the same graph for ease of comparison.

20 Figure 33 is the diffracting structure used for Figure 32.

Figure 34 is a cross-sectional diagram of the cellular structure of the diffracting structure shown in Fig 33.

25 Figure 35 is a preferred embodiment of a microphone array utilizing the methods and concepts of the invention.

Figure 36 is a plot of the beamformer response obtained using the microphone array of Figure 35 both
30 with and without a cellular structure and with optimization.

Variable	Mean	SD	Min	Max
Age	30.5	4.2	18	45
Gender	Male	1.0	0	1
Marital status	Married	1.0	0	1
Education	High school	1.0	0	1
Occupation	Unemployed	1.0	0	1
Income	Low	1.0	0	1
Health status	Good	1.0	0	1
Smoking status	Non-smoker	1.0	0	1
Alcohol consumption	Non-drinker	1.0	0	1
Exercise frequency	Low	1.0	0	1
Stress level	Low	1.0	0	1
Sleep quality	Good	1.0	0	1
Appetite	Good	1.0	0	1
Weight change	Stable	1.0	0	1
Blood pressure	Normal	1.0	0	1
Blood sugar	Normal	1.0	0	1
Cholesterol	Normal	1.0	0	1
Triglycerides	Normal	1.0	0	1
Hemoglobin A1c	Normal	1.0	0	1
Hemoglobin	Normal	1.0	0	1
White blood cells	Normal	1.0	0	1
Platelets	Normal	1.0	0	1
Red blood cells	Normal	1.0	0	1
Neutrophils	Normal	1.0	0	1
Lymphocytes	Normal	1.0	0	1
Monocytes	Normal	1.0	0	1
Eosinophils	Normal	1.0	0	1
Basophils	Normal	1.0	0	1
Prothrombin time	Normal	1.0	0	1
Partial thromboplastin time	Normal	1.0	0	1
Fibrinogen	Normal	1.0	0	1
Creatinine	Normal	1.0	0	1
BUN	Normal	1.0	0	1
Urea nitrogen	Normal	1.0	0	1
Glucose	Normal	1.0	0	1
Insulin	Normal	1.0	0	1
C-peptide	Normal	1.0	0	1
HbA1c	Normal	1.0	0	1
Hemoglobin	Normal	1.0	0	1
White blood cells	Normal	1.0	0	1
Platelets	Normal	1.0	0	1
Red blood cells	Normal	1.0	0	1
Neutrophils	Normal	1.0	0	1
Lymphocytes	Normal	1.0	0	1
Monocytes	Normal	1.0	0	1
Eosinophils	Normal	1.0	0	1
Basophils	Normal	1.0	0	1
Prothrombin time	Normal	1.0	0	1
Partial thromboplastin time	Normal	1.0	0	1
Fibrinogen	Normal	1.0	0	1
Creatinine	Normal	1.0	0	1
BUN	Normal	1.0	0	1
Urea nitrogen	Normal	1.0	0	1
Glucose	Normal	1.0	0	1
Insulin	Normal	1.0	0	1
C-peptide	Normal	1.0	0	1
HbA1c	Normal	1.0	0	1
Hemoglobin	Normal	1.0	0	1
White blood cells	Normal	1.0	0	1
Platelets	Normal	1.0	0	1
Red blood cells	Normal	1.0	0	1
Neutrophils	Normal	1.0	0	1
Lymphocytes	Normal	1.0	0	1
Monocytes	Normal	1.0	0	1
Eosinophils	Normal	1.0	0	1
Basophils	Normal	1.0	0	1
Prothrombin time	Normal	1.0	0	1
Partial thromboplastin time	Normal	1.0	0	1
Fibrinogen	Normal	1.0	0	1
Creatinine	Normal	1.0	0	1
BUN	Normal	1.0	0	1
Urea nitrogen	Normal	1.0	0	1
Glucose	Normal	1.0	0	1
Insulin	Normal	1.0	0	1
C-peptide	Normal	1.0	0	1
HbA1c	Normal	1.0	0	1
Hemoglobin	Normal	1.0	0	1
White blood cells	Normal	1.0	0	1
Platelets	Normal	1.0	0	1
Red blood cells	Normal	1.0	0	1
Neutrophils	Normal	1.0	0	1
Lymphocytes	Normal	1.0	0	1
Monocytes	Normal	1.0	0	1
Eosinophils	Normal	1.0	0	1
Basophils	Normal	1.0	0	1
Prothrombin time	Normal	1.0	0	1
Partial thromboplastin time	Normal	1.0	0	1
Fibrinogen	Normal	1.0	0	1</

In a microphone array the separate signals from the separate microphones are weighted and summed to provide an output signal. This process is represented by the equation:

10

w_m is the weight assigned to the particular microphones;

15

20

$$w_m = |w_m| e^{(+i\omega\tau_m)}$$

25

Useful beampatterns can be obtained by using a uniform weighting scheme, setting $|w_m|=1$ and choosing the

time delay τ_m so that all microphone contributions are in phase when sound comes from a desired direction. This approach is equivalent to delay-and-sum beamforming for an array in free space. When acoustical noise is present, improved beamforming performance can be obtained by applying optimization techniques, as discussed below.

The acoustic pressure signal p_m from microphone m consists of both a signal component s_m and a noise component n_m where

$$p_m = s_m + n_m$$

An array is designed to enhance reception of the signal component while suppressing reception of the noise component. The array's ability to perform this task is described by a performance index known as array gain.

Array gain is defined as the ratio of the array output signal-to-noise ratio over that of an individual sensor. For a specific frequency ω the array gain $G(\omega)$ can be written using matrix notation as

$$G(f) = \frac{E\{|W^H S|^2\} / (E\{|W^H N|^2\})}{\sigma_s^2 / \sigma_n^2} = \frac{E\{W^H S \cdot S^{HW}\} / \sigma_s^2}{E\{W^H N \cdot N^H W\} / \sigma_n^2} \quad (1)$$

In this expression, \mathbf{W} is the vector of sensor weights

$$W^T = [w_1(\omega)w_2(\omega)\dots w_M(\omega)],$$

S is the vector of signal components

5

$$S^T = [s_1(\omega)s_2(\omega)\dots s_M(\omega)],$$

N is the vector of noise components

10

$$N^T = [n_1(\omega)n_2(\omega)\dots n_M(\omega)],$$

σ_s^2 and σ_n^2 are the signal and noise powers observed at a selected reference sensor, respectively, and $E\{\}$ is the expectation operator.

By defining the signal correlation matrix $R_{ss}(\omega)$

15

$$R_{ss}(\omega) = E\{S \cdot S^H\} / \sigma_s^2 \quad (2)$$

and the noise correlation matrix $R_{nn}(\omega)$

$$R_{nn}(\omega) = E\{N \cdot N^H\} / \sigma_n^2 \quad (3)$$

20 the above expression for array gain becomes

$$G(\omega) = \frac{W^H R_{ss}(\omega) W}{W^H R_{nn}(\omega) W}. \quad (4)$$

The array gain is thus described as the ratio of two quadratic forms (also known as a Rayleigh quotient). It is well known in the art that such ratios can be maximized by proper selection of the weight vector W . Such maximization is advantageous in microphone array sound pickup since it can provide for enhanced array performance for a given number and spacing of microphones simply by selecting the sensor weights W .

10 Provided that $R_{nn}(\omega)$ is non-singular, the value of $G(\omega)$ is bounded by the minimum and maximum eigenvalues of the symmetric matrix $R_{nn}^{-1}(\omega) R_{ss}(\omega)$. The array gain is maximized by setting the weight vector W equal to the eigenvector corresponding to the maximum eigenvalue.

15 In the special case where $R_{ss}(\omega)$ is a dyad, that is, it is defined by the outer product

$$R_{ss}(\omega) = SS^H \quad (5)$$

then the weight vector W_{opt} that maximizes $G(\omega)$ is given
20 simply by

$$W_{opt} = R_{nn}^{-1}(\omega) S. \quad (6)$$

It has been shown that the optimum weight solutions for several different optimization strategies

can all be expressed as a scalar multiple of the basic solution

$$\mathbf{R}_{nn}^{-1}(\omega) \mathbf{S}.$$

5

The maximum array gain $G(\omega)_{\text{opt}}$ provided by the weights in (6) is

$$G(\omega)_{\text{opt}} = \mathbf{S}^H \mathbf{R}_{nn}^{-1}(\omega) \mathbf{S}. \quad (7)$$

10 Specific solutions for \mathbf{W}_{opt} are determined by the exact values of the signal and noise correlation matrices,

$$\mathbf{R}_{ss}(\omega) \text{ and } \mathbf{R}_{nn}(\omega).$$

15

Optimized beamformers have the potential to provide higher gain than available from delay-and-sum beamforming. Without further constraints, however, the resulting array can be very sensitive to the effects of microphone response tolerances and noise. In extreme cases, the optimum gain is impossible to realize using practical sensors.

20 A portion of the optimized gain can be realized, however, by modifying the optimization procedure. The design of an optimum beamformer then becomes a trade-off between the array's sensitivity to errors and the desired amount of gain over the spatial noise field. Two methods that provide robustness against errors are considered: gain maximization with a white-noise gain constraint and maximization of expected array gain.

25

30

Regarding gain maximization with a white-noise gain constraint, white noise gain is defined as the array gain against noise that is incoherent between sensors. The noise correlation matrix in this case
 5 reduces to an $M \times M$ identity matrix. Substituting this into the expression for array gain yields

$$G_w(\omega) = \frac{W^H R_{ss}(\omega) W}{W^H I W} \quad (8)$$

10 White noise gain quantifies the array's reduction of sensor and preamplifier noise. The higher the value of $G_w(\omega)$, the more robust the beamformer. As an example, the white noise gain for an M -element delay-and-sum beamformer steered for plane waves is M . In this case,
 15 array processing reduces uncorrelated noise by a factor of M (improves the signal-to-noise ratio by a factor of M).

A white noise gain constraint is imposed on the gain maximization procedure by adding a diagonal
 20 component to the noise correlation matrix. That is, replace $R_{nn}(\omega)$ by $R_{nn}(\omega) + \kappa I$. The strength of the constraint is controlled by the magnitude of κ . Setting κ to a large value implies that the dominant noise is uncorrelated from microphone to microphone. When
 25 uncorrelated noise is dominant, the optimum weights are those of a conventional delay-and-sum beamformer. Setting $\kappa = 0$, of course, produces the unconstrained optimum array. Unfortunately, there is no simple relationship between the constraint parameter κ and the

constrained value of white noise gain. Designing an array for a prescribed value of $G_w(\omega)$ requires an iterative procedure. The optimum weight vector is thus

5
$$W_{opt} = (R_{ss}(\omega) + \kappa I)^{-1} S$$

where it is assumed that $R_{ss}(\omega)$ is given by Equation 5.

Of course, a suitable value of $G_w(\omega)$ must be selected. This choice will depend on the exact level of sensor and preamplifier noise present. Lower sensor and preamplifier noise permits more white noise gain to be
10 traded for array gain. As an example, the noise level (in equivalent sound pressure level) provided by modern electret microphones is of the order of 20-30 dBSL (that is, dB re: 20×10^{-6} Pa) whereas the acoustic background
15 noise level of typical offices are in the vicinity of 30-45 dBSL. Since the uncorrelated sensor noise is about 10-15 dB lower than the acoustic background noise (due to the assumed noise field) it is possible to trade off some of the sensor SNR for increased rejection of
20 environmental noise and reverberation.

To maximize the expected array gain, the following analysis applies. For an array in free space, the effects of many types of microphone errors can be accommodated by constraining white noise gain. Since the
25 acoustic pressure observed at each microphone is essentially the same the levels of sensor noise and the effects of microphone tolerances are comparable between microphones. In the presence of a diffracting object, however, the pressure observed at a microphone on the
30 side facing the sound source may be substantially higher

than that observed in the acoustic shadow zone. This means that the relative importance of microphone noise varies substantially with the different microphone positions. Similarly, the effects of microphone gain and
 5 phase tolerances also vary widely with microphone location.

To obtain a practical design in the presence of amplitude and phase variations, an expression for the expected array gain must be obtained. The analysis of
 10 this problem is facilitated by assuming that the actual array weights described by the vector \mathbf{W} vary in amplitude and phase about their nominal values \mathbf{W}_0 . Assuming zero-mean, normally distributed fluctuations it is possible to evaluate the expected gain of the
 15 beamformer. The expression is

$$E\{G(\omega)\} = \frac{e^{-\sigma_p^2} (\mathbf{W}_0^H \mathbf{R}_{ss}(\omega) \mathbf{W}_0) + (1 - e^{-\sigma_p^2} + \sigma_m^2) (\mathbf{W}_0^H \text{diag}(\mathbf{R}_{ss}(\omega)) \mathbf{W}_0)}{e^{-\sigma_p^2} (\mathbf{W}_0^H \mathbf{R}_{mm}(\omega) \mathbf{W}_0) + (1 - e^{-\sigma_p^2} + \sigma_m^2) (\mathbf{W}_0^H \text{diag}(\mathbf{R}_{mm}(\omega)) \mathbf{W}_0)} \quad (9)$$

where σ_m^2 is the variance of the magnitude fluctuations and σ_p^2 is the variance of the phase fluctuations due to
 20 microphone tolerance.

Although this expression is more complicated than that shown in (4), it is still a ratio of two quadratic forms. Provided that the matrix \mathbf{A} is non-singular, the value of the ratio is bounded by the minimum and maximum
 25 eigenvalues of the symmetric matrix

$$\mathbf{A}^{-1} \mathbf{B}$$

where

$$A = \left(e^{-\sigma_p^2} R_{mm}(\omega) + \left(1 - e^{-\sigma_p^2} \right) \text{diag}(R_{mm}(\omega)) \right)$$

and

$$B = \left(e^{-\sigma_p^2} R_{ss}(\omega) + \left(1 - e^{-\sigma_p^2} + \sigma_m^2 \right) \text{diag}(R_{ss}(\omega)) \right)$$

The expected gain $E\{G(\omega)\}$ is maximized by setting
 5 the weight vector \mathbf{W}_0 equal to the eigenvector which
 corresponds to the maximum eigenvalue.

Notwithstanding the above optimization procedures,
 useful beampatterns can be obtained by using a uniform
 weighting scheme. This approach is equivalent to
 10 delay-and-sum beamforming for an array in free space.

In the following analyses, we will set the time
 delay τ_m so that all microphone contributions are in
 phase when sound comes from a desired direction and
 simply adopt unit amplitude weights $|\omega_m|=1$. The output
 15 of a 3 dimension array is then given by Equation 10:

$$V \propto \sum_{m=1}^m p_m e^{(+i\omega\tau_m)} \quad (10)$$

Two examples of such an array are shown in Figures
 1 and 2. Figure 1 shows a circular array 10 with a
 20 sound source 20 and a multiplicity of microphones 30.
 Figure 2 shows a tetrahedral microphone array 40 with
 microphones 30 located at each vertex.

For the circular array 10, a source located at a
 position (r_o, θ_o, ϕ_o) (with
 25 r_o = distance from the center of the array

θ_o = angle to the positive z-axis as shown in
Figure 1

ϕ_o = angle to the positive x-axis as shown in
Figure 1)

5 the pressures at each microphone 30 is given by Equation
11:

$$p_{mo} = \frac{C \exp(ikr_{mo})}{kr_{mo}}, \quad (11)$$

10 where C is a source strength parameter and the distances
between source and microphones are

$$r_{mo} = [r_o^2 + a^2 - 2r_o a \sin \theta_o \cos(\phi_m - \phi_o)]^{1/2};$$

15 where a is the radius of the circle, ϕ_m is the azimuthal
position of microphone m. The array output is thus
given by Equation 12:

$$V \propto \sum_{m=1}^m p_{mo} e^{(+i\omega\tau_m)} \quad (12)$$

20 Suppose it is desired to steer a beam to a look
position (r_l, θ_l, ϕ_l) , where θ_l is the azimuth and ϕ_l
is the elevation angle. The pressure p_m that would be
obtained at each microphone position if the source was
at this look position are

25

$$p_{ml} = \frac{C \exp(ikr_{ml})}{kr_{ml}}$$

where

$$r_{ml} = [r_l^2 + a^2 - 2r_l a \sin \theta_l \cos(\phi_m - \phi_l)]^{1/2}$$

5

To bring all the contributions into phase when the look position corresponds to the actual source position, the phase of the weights need to be set so that

10

$$\omega \tau_m = -kr_{ml}$$

The beamformer output is then given by Equation 13:

$$V \propto \sum_{m=1}^M \frac{\exp[ik(r_{mo} - r_{ml})]}{kr_{mo}} \quad (13)$$

15

A sample response function is shown in Figure 3. A 5-element circular array of 8.5cm diameter located in free space has been assumed. The source is located at a range of 2m and at an angular positions of $\phi_0 = 0$ and $\theta_0 = \pi/2$. For the look position, $r_l = 2m$, $\theta_l = \pi/2$ and the azimuth ϕ_l is varied. It should be noted that the directional beam response pictured in Figure 3 is for a frequency of 650 Hz and that uniform weights have been assumed.

The response function in Figure 3 can be improved upon by inserting a diffracting structure inside the array. An example of this is pictured in Figure 4.

Figure 4 illustrates a circular array with a spherical diffracting structure positioned within the array.

Figure 5 illustrates another configuration using a diffracting structure. Figure 5 shows a bi-circular array 50 with a diffracting structure 60 mostly contained within the space defined by the bi-circular array 50.

To determine the response function for an array such as that pictured in Figure 4, some of the assumptions made in calculating the response function shown in Figure 3 cannot be made. While the above equations assume that the pressure at each microphone was the free-field sound pressure due to a point source, such is not the case with an array having a diffracting structure. A diffracting structure should have a surface S that can be defined by an acoustic impedance function. Subject to the appropriate boundary conditions on the surface S of the diffracting structure 60, the acoustic wave equation will have to be solved to determine the sound pressure over the surface. Diffraction and scattering effects can then be included in the beamforming analysis.

For such an analysis, a source at a position given by $\mathbf{r}_0 = (r_0, \theta_0, \phi_0)$ is assumed. For this source, the boundary value problem is given by Equation 14:

$$\nabla^2 p + k^2 p = \delta(\mathbf{r} - \mathbf{r}_0) \quad (14)$$

outside the surface S of the diffracting structure 60 ,
subject to the impedance boundary condition is given by
Equation 15:

5

$$\left[\frac{dp}{dn} + ik\beta p \right]_s = 0, \quad (15)$$

where n is the outward unit normal and β is the
10 normalized specific admittance. Asymptotically near the
source, the pressure is given by Equation 16:

$$p \rightarrow \frac{C \exp[ik|r - r_o|]}{k|r - r_o|} \quad (16)$$

15 Solutions for a few specific structures can be expressed
analytically but generally well known numerical
techniques are required. Regardless, knowing that a
solution does exist, we can write down a solution
symbolically as

20

$$p(r) = F(r, r_o),$$

where $F(r, r_o)$ is a function describing the solution in
two variables r and r_o .

25

Evaluating the pressure p_{m0} at each microphone position r_m we have:

$$p_{m0} = F(r_m, r_o)$$

5

giving a uniform weight beamformer output (Equation 17)

$$V \propto \sum_{m=1}^M F(r_m, r_o) \exp(i\omega\tau_m) \quad (17)$$

10

The pressure at each microphone will vary significantly in both magnitude and phase because of diffraction.

Suppose that a beam is to be steered toward a look
15 position $r_l = (r_l, \theta_l, \phi_l)$. The microphone pressures that would be obtained if this look position corresponded to the actual source position would be

$$p_{ml} = F(r_m, r_l)$$

20

The time delays τ_m are then set according to Equation 18

$$\omega\tau_m = -\arg[F(r_m, r_l)] \quad (18)$$

where $\arg[F(r_m, r_l)]$ denotes the argument of the function
25 $F(r_m, r_l)$.

As noted above, Figure 4 shows an example of the above. Figure 4 is a circular array 70 on the

circumference of a rigid surface 80. The solution for the sound field about a rigid sphere due to a point source is known in the art. For a source with free-field sound field as given by Equation 16, the total
5 sound field is given by Equation 19:

$$F(r, r_0) = iC \sum_{n=0}^{\infty} (2n+1) P_n(\cos \psi) h_n^{(1)}(kr_>) [j_n(kr_<) - a_n h_n^{(1)}(kr_<)] \quad (19)$$

where ψ is the angle between vectors r and r_0 , P_n is the
10 Legendre polynomial of order n , j_n is the spherical Bessel function of the first kind and order n , $h_n^{(1)}$ is the spherical Hankel function of the first kind and order n , $r_< = \min(r, r_0)$, $r_> = \max(r, r_0)$, and

$$15 \quad a_n = j'_n(ka) / h_n^{(1)}(ka),$$

where the ' indicates differentiation with respect to the argument kr . To obtain $F(r, r_1)$, r_1 is used in place of r_0 in Equation 19. The solutions can be evaluated at
20 each microphone position $r = r_m$.

This solution is then used in the evaluation of the beamformer output V . For a circular array 8.5cm in diameter with 5 equally spaced microphones in the X-Y plane forming the array and on the circumference of an
25 acoustically rigid sphere, the response function is shown in Figure 6.

For the response function shown in Figure 6, a

650Hz point source was located in the plane of the microphones with $r_0=2$, $\theta_0= \pi/2$, and $\phi_0=0$. The look position has $r_l = 2m$ and $\theta_l = \pi/2$ fixed. The response V as a function of azimuthal look angle ϕ_l is shown as the solid line in Figure 6. For comparison, the beamformer response obtained with no sphere has been calculated using Equation 13 and this result shown as the dashed line in Figure 6.

The inclusion of the diffracting sphere is seen to enhance the performance of the array by reducing the width of the central beam.

While the circular array was convenient for its mathematical tractability, many other shapes are possible for both the microphone array and the diffracting structure. Figures 7 to 24 illustrate these possible configurations.

The configurations pictured with a top view and a side view are as follows:

	Microphone Array	Diffracting Structure
Figures 7A & B	Circular	hemisphere
Figures 8A & B	bi-circular	hemisphere
Figures 9A & B	circular	right circular cylinder
Figures 10A & B	circular	raised right circular cylinder
Figures 11A & B	circular	cylinder with a star shaped cross section
Figures 12A & B	square pyramid	truncated square pyramid

5

Figures 13A & B	square	inverted truncated square pyramid with a generally square cross section
Figures 14A & B	circular	right circular cylinder having an oblate spheroid at each end
Figures 15A & B	circular	raised oblate spheroid
Figure 16A & B	circular	flat shallow solid cylinder raised from a surface
Figure 17A & B	circular	shallow solid cylinder having a convex top & being raised from a surface
Figure 18A & B	circular	circular shape with a convex top and a truncated cone as its base
Figure 19A & B	circular	shallow cup shaped cross section raised from a surface
Figure 20A & B	circular	shallow solid cylinder with a flared bottom

Figure 21A & B	square	circular shape with a convex top and a flared square base opening to the circular shape
Figure 22A & B	square	truncated square pyramid
Figure 23A & B	hexagonal	truncated hexagonal pyramid
Figure 24A & B	hexagonal	shallow hexagonal solid cylinder raised from the surface by a hexagonal stand

5

It should be noted that in the above described figures, the black dots denote the position of microphones in the array. Other shapes not listed above are also possible for the diffracting structure.

10

As can be seen from Figures 7 to 24, the placement of the microphone array can be anywhere as long as the diffracting structure, or at least a portion of it, is contained within the space defined by the array.

15

To determine the improvement in spatial response due to a diffracting structure, the directivity index D is used. This index is the ratio of the array response in the signal direction to the array response averaged over all directions. This index is given by equation 20:

$$D = 10 \log \left\{ \frac{|V(r_o)/r_o|^2}{\frac{1}{4\pi} \int_0^{2\pi} \int_0^\pi |V(r_\infty)/r_\infty|^2 \sin \theta d\theta d\phi} \right\} \quad (20)$$

and is expressed in decibels. The numerator gives the beamformer response when the array is directed toward the source, at range r_o ; the denominator gives the average response over all directions. This expression is mathematically equivalent to that provided for array gain if a spherically isotropic noise model is used for $R_{nn}(\omega)$.

Using this expression for the conditions presented in Figure 6, a directivity of 2.3 dB is calculated for the circular array with a sphere present; without the sphere the directivity is 0.9 dB. At a frequency of 650 Hz, the inclusion of a diffracting sphere improves the directivity by 1.4dB. The directivity for other frequencies has been calculated and presented in Figure 25. It is seen that improvements of at least 2 dB in directivity index are achieved in the 800-1600 Hz range.

Another consequence of an increase in directivity is the reduction in size that becomes possible for a practical device. Comparing the two curves in Figure 25, we see that with the sphere present, the array performs as well at 500Hz as the array without the sphere would perform at 800Hz, a ratio of 1.6; at higher frequencies, this ratio is about 1.2. It is known that the performance of an array depends on the ratio of size to wavelength. Hence, the array with the sphere could

be reduced in size by a factor of 1.4 and have approximately the same performance as the array with no sphere. This 30% reduction in size would be very important to designers of products such as handsfree
5 telephones or arrays for hearing aids where a smaller size is important. Moreover, once the size is reduced, the number of microphones could be reduced as well.

Additional performance enhancements can be obtained by appropriate treatment of the surface of the
10 diffracting objects. The surfaces need not be acoustically-rigid as assumed in the above analysis. There can be advantages in designing the exterior surfaces to have an effective acoustical surface impedance. Introducing some surface damping (especially
15 frequency dependent damping) could be useful in shaping the frequency response of the beamformer. There are however, particular advantages in designing the surface impedance so that the air-coupled surface waves can propagate over the surface. These waves travel at a
20 phase speed lower than the free-field sound speed. Acoustic signals propagating around a diffracting object via these waves will have an increased travel time and thus lead to a larger effective aperture of an array.

The existence and properties of air-coupled
25 surface waves are known in the art. A prototypical structure with a plurality of adjacent cells is shown in Figure 26. A sound wave propagating horizontally above this surface interacts with the air within the cells and has its propagation affected. This may be understood in
30 terms of the effective acoustic surface impedance Z of the structure. Plane-wave-like solutions of the Helmholtz equation,

$$p \propto e^{i\alpha x} e^{i\beta y}$$

for the sound pressure p , are sought subject to the boundary condition

5

$$\left(\frac{dp}{dy} + \frac{i\rho\omega}{Z} p \right)_{y=0} = 0 ,$$

where x and y are coordinates shown in Figure 26, $k = \omega/c$ is the wave number, ω is the angular frequency, ρ is the
 10 air density, $i = \sqrt{-1}$, and an $\exp(-i\omega t)$ time dependence is assumed. Then, the terms α and β in the Helmholtz equation are given by

$$\alpha/k = \sqrt{1 - (\rho c/Z)^2}$$

15 and

$$\beta/k = -\rho c/Z .$$

For a surface wave to exist, the impedance Z must have a
 20 spring-like reactance X , i.e., for $Z = R + iX$, $X > 0$ is required. Moreover, for surface waves to be observed practically, we require $R < X$ and $2 < X/\rho c < 6$. The surface wave is characterized by an exponential decrease in amplitude with height above the surface.

25 If the lateral size of the cells is a sufficiently small fraction of a wavelength of sound, then sound

propagation within the cells may be assumed to be one dimensional. For the simple cells of depth L shown in Figure 17, the effective surface impedance is

$$Z = ipc \cot kL,$$

so surface waves are possible for frequencies less than the quarter-wave resonance.

To exploit the surface-wave effect, microphones
 10 may be mounted anywhere along the length of the cells. At frequencies near cell resonance, however, the acoustic pressure observed at the cell openings and at other pressure nodal points will be very small. To use the microphone signals at these frequencies, the
 15 microphones should be located along the cell's length at points away from pressure nodal points. This can be achieved for all frequencies if the microphones are located at the bottom of the cells since an acoustically rigid termination is always an antinodal point.

20 The phase speed of a propagating surface wave is

$$c_{ph} = \omega / \operatorname{Re}\{ \alpha \}$$

For the simple surface structure shown in Figure 26, using a cell depth of L=2.5 cm, we obtain the phase
 25 speed shown in Figure 27. The phase speed is the free-field sound speed at low frequencies but drops gradually to zero at about 3400 Hz. Above this frequency, the reactance is negative and no surface wave can propagate. The reduced phase speed increases the travel time for

acoustic signals to propagate around the structure and results in improved beamforming performance.

Figures 28-31 show a few alternatives that the surface of a diffracting structure can be treated to generate surface waves. For these, a hemispherical structure has been adopted for simplicity but, as suggested in Figures 9-24, many other structures are possible. In Figure 28, the entire surface supports the formation of surface waves. The introduction of the surface treatment to a diffracting structure need not be uniform over its surface and advantages in directionality may be achievable by restricting the application. In Figure 29, the surface wave treatment is restricted to a band about the lower circumference; increased directivity would be anticipated for sources located closer to the horizontal plane through the hemisphere. Further reduction in scope, to provide increased directivity for a smaller range of source positions, is shown in Figure 30. The use of absorbing materials or treatment may also be useful. An absorbing patch on the top of the hemisphere, to reduce contributions from acoustic propagation over the top of the structure is shown in Figure 31.

The effect of such a surface treatment on the beam pattern of a 6-microphone delay-and-sum beamformer mounted on a hemisphere 90 8.5 cm in diameter is shown in Figure 32. The hemisphere 90 is shown in Figure 33 and is mounted on a reflecting plane 100 and the microphones 110 are equally spaced around the circumference of the hemisphere at the bottom of the cells 120. The cross sectional structure of the cells 120 are shown in Figure 34. The 10cm cells give a

surface impedance, at the hemisphere surface, that is spring-like at 650 Hz. For the response patterns shown in Figure 32, a 650 Hz point source was located in the plane of the microphones 110 with $r_0 = 2$, $\theta_1 = \pi/2$, and $\phi_0 = 0$. The look position has $r_l = 2m$ and $\theta_l = \pi/2$ fixed. The response V as a function of azimuthal look angle ϕ_l is shown as the solid line in Figure 32. The dashed line shows the response obtained for a rigid hemisphere with the microphones located on the outer surface at the base of the hemisphere.

The inclusion of the surface treatment is seen to enhance the array performance substantially. The width of the main beam at half height is reduced from $\pm 147^\circ$ for the rigid sphere to $\pm 90^\circ$ for the soft sphere. Furthermore, the directivity index at 650 Hz increases by 2.4dB.

The cellular surface described is one method for obtaining a desired acoustical impedance. This approach is attractive since it is completely passive and the impedance can be controlled by modifying the cell characteristics but there are practical limitations to the impedance that can be achieved.

Another method to provide a controlled acoustical impedance is the use of active sound control techniques. By using a combination of acoustic actuator (e.g. loudspeaker), acoustic sensor (e.g. microphone) and the appropriate control circuitry a wider variety of impedance functions can be implemented. (See for example US Patent number 5812686).

A design which encompasses the concepts disclosed above is depicted in Fig. 35. The design in Fig 35 is of a diffracting structure with a convex top 130 and an

inverted truncated cone 140 as its base. The inverted truncated cone 140 has, at its narrow portion, a cellular structure 150 which serves as the means to introduce an acoustical impedance. As will be noted below, the microphones are located inside the cells. The maximum diameter is 32 cm, the bottom diameter is 10 cm. This unit is designed to rest on a table top 160 which serves as a reflecting plane. The sloping sides of the truncated cone 140 make an angle of 38° with the table top. There are 3 rows of cells circling the speakerphone, each row containing 42 vertical cells. The 3 rows have a cell depth of 9.5 cm: these are the cells that were introduced to produce the appropriate acoustical surface impedance. To accommodate the cells, the top of the housing had to be 15 cm above the table top. Included in this height is 2.9 mm for an O-ring 170 on the bottom. The separators between the cells are 2.5 mm thick. Six microphones were called for in this design, to be located in 6 equally-spaced cells of the bottom row, at the top, innermost position in the cells. The o-ring 170 prevents sound waves from leaking via the underside, from one side of the cone 140 to the other. The table top 160 acts as a reflecting surface from which sound waves are reflected to the cells. Also included in the design is a speaker placement 180 at the top of the convex top 130.

The array beamforming is based on, and makes use of, the diffraction of incoming sound by the physical shape of the housing. Computation of the sound fields about the housing, for various source positions and sound frequencies from 300 Hz to 4000Hz, was conveniently performed using a boundary element

technique. Directivity indices achieved using delay-and-sum and optimized beamforming are shown in Figure 36 as a function of frequency. Results are shown for the housing with no cells (dashed line) as well as
5 for the housing with three rows of cells open as described above (solid line). Also shown are results for the housing with cells and optimization (dash and dot lines). As seen in Figure 36, the use of cells to control the surface impedance has a beneficial effect on
10 the directivity index. An increase in directivity index is observed between 550 Hz to 1.6kHz with a boost of approximately 4 dB obtained in the range of 700Hz to 800Hz. The use of array-gain optimization, as described by equation 9, is shown in Figure 36 to further increase
15 the directivity of the device by approximately 6 dB at 200 Hz.

The person understanding the above described invention may now conceive of alternative design, using the principles described herein. All such designs which
20 fall within the scope of the claims appended hereto are considered to be part of the present invention.

The embodiments of the invention in which an exclusive property or privilege is claimed are defined as follows:

1. A diffracting structure for use with a microphone array, the microphone array being comprised of a plurality of microphones defining a space generally enclosed by the array wherein a placement of the
5 structure is chosen from the group comprising:
 - a) the structure is positioned substantially adjacent to the space;
 - b) at least a portion of the structure is substantially within the space; and
10 wherein the structure has an outside surface.
2. A structure as claimed in claim 1 wherein a first set of portions of the outside surface of the structure is constructed and arranged to allow air-
15 coupled surface waves to propagate over the first set of portions.
3. A structure as claimed in claim 2 wherein a second set of portions of the outside surface of the structure is constructed and arranged to absorb and dampen sound.
4. A structure as claimed in claim 1 wherein the outside surface of the structure is constructed and arranged to allow air-coupled surface waves to propagate over the outside surface.

5. A structure as claimed in claim 2 wherein the first set of portions has a cell-like construction.

6. A structure as claimed in claim 4 wherein the outside surface of the structure has a cell-like construction.

7. A structure as claimed in claim 1 wherein the structure has a shape chosen from the group comprising:

- a) hemisphere
- b) right circular cylinder
- 5 c) a cylinder with a star shaped cross section
- d) a square truncated pyramid
- e) an inverted truncated pyramid with a generally square cross section
- f) a right circular cylinder coupled to a
- 10 flattened oblate spheroid at each end of the cylinder
- g) an oblate spheroid
- h) a flat shallow solid cylinder
- i) a shallow solid cylinder with a convex top
- j) generally circular with a convex top
- 15 k) shallow cup shaped cross section
- l) shallow solid cylinder
- m) generally circular with a convex top
- n) hexagonal truncated pyramid and
- o) shallow hexagonal solid cylinder

8. A structure as claimed in claim 7 wherein the outside surface of the structure has a cell-like construction.

9. A structure as claimed in claim 7 wherein the structure is raised from a surface by a support having a shape chosen from the group comprising:

- 5 aa) circular right cylinder
- bb) square cylinder
- cc) flaring cylinder with a narrow portion adjacent to the surface
- dd) a square base attached to a flaring cylinder
- 10 and
- ee) hexagonal cylinder

10. A structure as claimed in claim 9 wherein the outside surface of the structure has a cell-like construction.

11. A microphone array comprising:
- a plurality of microphones constructed and arranged to generally enclose a space; and
 - a diffracting structure placed such that at least
- 5 a portion of the structure is adjacent to said space and wherein the diffracting structure has an outside surface.

12. An array as claimed in claim 11 wherein at least a portion of the structure is substantially within the space.

13. An array as claimed in claim 11 wherein a first set of portions of the outside surface of the structure is constructed and arranged to allow air-

coupled surface waves to propagate over a first set of portions.

14. An array as claimed in claim 13 wherein a second set of portions of the outside surface of the structure is constructed and arranged to absorb and dampen sound.

15. An array as claimed in claim 11 wherein the outside surface of the structure is constructed and arranged to allow air-coupled surface waves to propagate over the outside surface.

16. An array as claimed in claim 13 wherein the first set of portions has a cell-like construction.

17. An array as claimed in claim 15 wherein the outside surface of the structure has a cell-like construction.

18. An array as claimed in claim 11 wherein a shape of the structure is chosen from the group comprising:

- a) hemisphere
- 5 b) right circular cylinder
- c) a cylinder with a star shaped cross section
- d) a square truncated pyramid
- e) an inverted truncated pyramid with a generally square cross section
- 10 f) a right circular cylinder coupled to a flattened oblate spheroid at each end of the cylinder
- g) an oblate spheroid and
- h) a flat shallow solid cylinder

- 15 i) a shallow solid cylinder with a convex top
j) generally circular with a convex top
k) shallow cup shaped cross section
l) shallow solid cylinder
m) generally circular with a convex top
n) hexagonal truncated pyramid and
20 o) shallow hexagonal solid cylinder
and wherein the plurality of microphones is arranged in
a configuration chosen from the group comprising:
a) generally circular
b) generally bi-circular
25 c) generally tetrahedral
d) triangular
e) bi-triangular.

19. An array as claimed in claim 18 wherein the
outside surface of the structure has a cell-like
construction.

20. An array as claimed in claim 19 wherein the
structure is raised from a surface by a support having a
shape chosen from the group comprising:

- 5 aa) right circular cylinder
bb) square cylinder
cc) flaring cylinder with a narrow portion adjacent
to the surface
dd) a square base attached to a flaring cylinder
10 and
ee) hexagonal cylinder

21. An array as claimed in claim 20 wherein the outside surface of the structure has a cell-like construction and wherein the microphones are disposed within the cells.

22. A method of increasing an apparent aperture size of a microphone array, the method comprising:

- 5 a) positioning a diffraction structure within a space defined by the microphone array to extend a travel time of sound signals to be received by microphones in the microphone array;
- b) generating different time delay weights, phases, and amplitudes for signals from each microphone in the microphone array;
- 10 c) applying said time delay weights to said sound signals received by each microphone in the microphone array

wherein

- the diffraction structure has a shape;
- 15 said time delay weights are determined by analyzing the shape of the diffraction structure and the travel time of the sound signals.

23. A method as claimed in claim 16 wherein the shape of the structure is chosen from the group comprising:

- a) hemisphere
- 5 b) right circular cylinder
- c) a cylinder with a star shaped cross section
- d) a truncated square pyramid
- e) an upside down truncated square pyramid

- 10 f) a right circular cylinder coupled to a flattened
oblate spheroid at each end of the cylinder
g) an oblate spheroid
h) a flat shallow solid cylinder
i) a shallow solid cylinder with a convex top
j) generally circular with a convex top
15 k) shallow cup shaped cross section
l) shallow solid cylinder
m) generally circular with a convex top
n) hexagonal truncated pyramid and
o) shallow hexagonal solid cylinder

24. A method as claimed in claim 22 further
including constructing and arranging a first set of
portions of an outside surface of the diffraction
structure to allow air-coupled surface waves to
5 propagate over the first set of portions.

25. A method as claimed in claim 24 further
including constructing and arranging a second set of
portions of the outside surface of the diffraction
structure to absorb and dampen the sound signals.

26. A method as claimed in claim 22 further
including constructing and arranging an outside surface
of the diffraction structure to allow air-coupled
surface waves to propagate over the outside surface.

27. A method as claimed in claim 24 further
including constructing and arranging the first set of
portions of the surface of the diffraction structure to
have a cell-like construction.

28. A method as claimed in claim 26 further including constructing and arranging the outside surface of the diffraction structure to have a cell-like construction.

29. A microphone array for use on a generally flat surface comprising:

a body having a convex top and an inverted truncated cone for a bottom;

5 a plurality of cells located on a surface of the bottom for producing an acoustic impedance; and

a plurality of microphones located adjacent to the bottom.

30. A microphone array as claimed in claim 29 wherein each of the plurality of microphones is placed inside a cell chosen from the plurality of cells.

31. A microphone array as claimed in claim 29 further including a speaker located substantially in a center of the convex top.

ABSTRACT

The present invention increases the aperture size of a microphone array by introducing a diffracting structure into the interior of a microphone array. The diffracting structure within the array modifies both the amplitude and phase of the acoustic signal reaching the microphones. The diffracting structure increases acoustic shadowing along with the signal's travel time around the structure. The diffracting structure in the array effectively increases the aperture size of the array and thereby increases the directivity of the array. Constructing the surface of the diffracting structure such that surface waves can form over the surface further increases the travel time and modifies the amplitude of the acoustical signal thereby allowing a larger effective aperture for the array.




FIG 1




FIG 2




FIG 3




FIG 4




FIG 5




FIG 6




FIG 7A




FIG 7B




FIG 8A




FIG 8B




FIG 9A




FIG 9B




FIG 10A




FIG 10B




FIG 11A




FIG 11B




FIG 12A



FIG 12B




FIG 13A




FIG 13B




FIG 14A




FIG 14B




FIG 15A




FIG 15B




FIG 16A




FIG 16B




FIG 17A




FIG 17B




FIG 18A



FIG 18B




FIG 19A



FIG 19B




FIG 20A




FIG 20B




FIG 21A




FIG 21B




FIG 22A




FIG 22B




FIG 23A




FIG 23B




FIG 24A




FIG 24B




FIG 25




FIG 26




FIG 27




FIG 28




FIG 29




FIG 30




FIG 31




FIG 32




FIG 33




FIG 34




FIG 35




FIG 36

Please type a plus sign (+) inside this box → +

PTO/SB/01 (12-97)

Approved for use through 9/30/00. OMB 0651-0032
Patent and Trademark Office; U.S. DEPARTMENT OF COMMERCE

Under the Paperwork Reduction Act of 1995, no persons are required to respond to a collection of information unless it contains a valid OMB control number.

DECLARATION FOR UTILITY OR DESIGN PATENT APPLICATION (37 CFR 1.63)	Attorney Docket Number	473P09US
	First Named Inventor	Stinson, Michael R.
	COMPLETE IF KNOWN	
	Application Number	/
	Filing Date	
	Group Art Unit	
<input checked="" type="checkbox"/> Declaration Submitted with Initial Filing	OR	<input type="checkbox"/> Declaration Submitted after Initial Filing (surcharge (37 CFR 1.16 (e)) required)
	Examiner Name	

As a below named inventor, I hereby declare that:

My residence, post office address, and citizenship are as stated below next to my name.

I believe I am the original, first and sole inventor (if only one name is listed below) or an original, first and joint inventor (if plural names are listed below) of the subject matter which is claimed and for which a patent is sought on the invention entitled:

MICROPHONE ARRAY DIFFRACTING STRUCTURE

the specification of which (Title of the Invention)

☒ is attached hereto
OR
☐ was filed on (MM/DD/YYYY) as United States Application Number or PCT International Application Number and was amended on (MM/DD/YYYY) (if applicable).

I hereby state that I have reviewed and understand the contents of the above identified specification, including the claims, as amended by any amendment specifically referred to above.

I acknowledge the duty to disclose information which is material to patentability as defined in 37 CFR 1.56.

I hereby claim foreign priority benefits under 35 U.S.C. 119(a)-(d) or 365(b) of any foreign application(s) for patent or inventor's certificate, or 365(a) of any PCT international application which designated at least one country other than the United States of America, listed below and have also identified below, by checking the box, any foreign application for patent or inventor's certificate, or of any PCT international application having a filing date before that of the application on which priority is claimed.

Prior Foreign Application Number(s)	Country	Foreign Filing Date (MM/DD/YYYY)	Priority Not Claimed	Certified Copy Attached?	
				YES	NO
			<input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/>	<input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/>	<input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/>

☐ Additional foreign application numbers are listed on a supplemental priority data sheet PTO/SB/02B attached hereto:

I hereby claim the benefit under 35 U.S.C. 119(e) of any United States provisional application(s) listed below.

Application Number(s)	Filing Date (MM/DD/YYYY)	<input type="checkbox"/> Additional provisional application numbers are listed on a supplemental priority data sheet PTO/SB/02B attached hereto.
60/112,950	12/18/1999	

[Page 1 of 2]

Burden Hour Statement: This form is estimated to take 0.4 hours to complete. Time will vary depending upon the needs of the individual case. Any comments on the amount of time you are required to complete this form should be sent to the Chief Information Officer, Patent and Trademark Office, Washington, DC 20231. **DO NOT SEND FEES OR COMPLETED FORMS TO THIS ADDRESS. SEND TO:** Assistant Commissioner for Patents, Washington, DC 20231.

Please type a plus sign (+) inside this box → +

PTO/SB/01 (12-97)
Approved for use through 9/30/00. OMB 0651-0032
Patent and Trademark Office; U.S. DEPARTMENT OF COMMERCE

Under the Paperwork Reduction Act of 1995, no persons are required to respond to a collection of information unless it contains a valid OMB control number.

DECLARATION — Utility or Design Patent Application

I hereby claim the benefit under 35 U.S.C. 120 of any United States application(s), or 365(c) of any PCT international application designating the United States of America, listed below and, insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States or PCT international application in the manner provided by the first paragraph of 35 U.S.C. 112, I acknowledge the duty to disclose information which is material to patentability as defined in 37 CFR 1.56 which became available between the filing date of the prior application and the national or PCT international filing date of this application.

U.S. Parent Application or PCT Parent Number	Parent Filing Date (MM/DD/YYYY)	Parent Patent Number (if applicable)

☐ Additional U.S. or PCT international application numbers are listed on a supplemental priority data sheet PTO/SB/02B attached hereto.

As a named inventor, I hereby appoint the following registered practitioner(s) to prosecute this application and to transact all business in the Patent and Trademark Office connected therewith:

☐ Customer Number

OR

☒ Registered practitioner(s) name/registration number listed below

Place Customer
Number Bar Code
Label here

Name	Registration Number	Name	Registration Number
R.A. Wilkes	28170		
H.C. Baker	19333		
R.G. Hendry	22927		

☐ Additional registered practitioner(s) named on supplemental Registered Practitioner Information sheet PTO/SB/02C attached hereto.

Direct all correspondence to: ☐ Customer Number OR ☒ Correspondence address below

Name	Pascal & Associates				
Address	P.O. Box 11121				
Address	Station H				
City	Nepean	State	Ontario	ZIP	K2H 7T8
Country	Canada	Telephone	(613) 820-1366	Fax	(613) 820-1553

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under 18 U.S.C. 1001 and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.

Name of Sole or First Inventor:		<input type="checkbox"/> A petition has been filed for this unsigned inventor	
Given Name (first and middle (if any))		Family Name or Surname	
Michael R.		Stinson	
Inventor's Signature	<i>Mike Stinson</i>		Date <i>Dec 15, 1999</i>
Residence: City	Gloucester	State	Ontario Country Canada Citizenship CA
Post Office Address			
Post Office Address	608 Duff Crescent		
City Gloucester	State Ontario	ZIP K1J 7C5	Country Canada

☐ Additional inventors are being named on the supplemental Additional Inventor(s) sheet(s) PTO/SB/02A attached hereto

Please type a plus sign (+) inside this box → +

PTO/SB/02A (3-97)
Approved for use through 9/30/98. OMB 0651-0032
Patent and Trademark Office; U.S. DEPARTMENT OF COMMERCE

Under the Paperwork Reduction Act of 1995, no persons are required to respond to a collection of information unless it contains a valid OMB control number.

DECLARATION

ADDITIONAL INVENTOR(S)
Supplemental Sheet
Page 2 of 2

Name of Additional Joint Inventor, if any:

☐ A petition has been filed for this unsigned inventor

Given Name (first and middle [if any])

Family Name or Surname

James G.

Ryan

Inventor's
Signature

James G. Ryan

Date

DEC. 15/99

Residence: City

Gloucester

State

ON

Country

Canada

Citizenship

CA

Post Office Address

Post Office Address

6135 Lariviere Crescent

City

Gloucester

State

Ontario

ZIP

K1W 1C6

Country

Canada

Name of Additional Joint Inventor, if any:

☐ A petition has been filed for this unsigned inventor

Given Name (first and middle [if any])

Family Name or Surname

Inventor's
Signature

Date

Residence: City

State

Country

Citizenship

Post Office Address

Post Office Address

City

State

ZIP

Country

Name of Additional Joint Inventor, if any:

☐ A petition has been filed for this unsigned inventor

Given Name (first and middle [if any])

Family Name or Surname

Inventor's
Signature

Date

Residence: City

State

Country

Citizenship

Post Office Address

Post Office Address

City

State

ZIP

Country

Burden Hour Statement: This form is estimated to take 0.4 hours to complete. Time will vary depending upon the needs of the individual case. Any comments on the amount of time you are required to complete this form should be sent to the Chief Information Officer, Patent and Trademark Office, Washington, DC 20231. DO NOT SEND FEES OR COMPLETED FORMS TO THIS ADDRESS. SEND TO: Assistant Commissioner for Patents, Washington, DC 20231.